

Help Listing

```
[user9@DE601C StationConfigs]$ rspctl --help
rspctl usage:
```

```
--- RCU control -----
-----
```

```
rspctl --rcu                [--select=<set>] # show current rcu
control setting
```

```
rspctl --rcu=0x00000000    [--select=<set>] # set the rcu
control registers
```

```
mask      value
0x0000007F INPUT_DELAY  Sample delay for the data from the RCU.
0x00000080 INPUT_ENABLE Enable RCU input.
```

```
0x00000100 LBL-EN      supply LBL antenna on (1) or off (0)
0x00000200 LBH-EN      supply LBH antenna on (1) or off (0)
0x00000400 HB-EN      supply HB on (1) or off (0)
0x00000800 BANDSEL    low band (1) or high band (0)
0x00001000 HB-SEL-0   HBA filter selection
0x00002000 HB-SEL-1   HBA filter selection
```

```
Options : HBA-SEL-0 HBA-SEL-1 Function
          0          0      210-270 MHz
          0          1      170-230 MHz
          1          0      110-190 MHz
          1          1      all off
```

```
0x00004000 VL-EN      low band supply on (1) or off (0)
0x00008000 VH-EN      high band supply on (1) or off (0)
```

```
0x00010000 VDIG-EN    ADC supply on (1) or off (0)
0x00020000 LBL-LBH-SEL LB input selection 0=LBL, 1=LBH
0x00040000 LB-FILTER  LB filter selection
          0      10-90 MHz
          1      30-80 MHz
```

```
0x00080000 ATT-CNT-4  on (1) is 1dB attenuation
0x00100000 ATT-CNT-3  on (1) is 2dB attenuation
0x00200000 ATT-CNT-2  on (1) is 4dB attenuation
0x00300000 ATT-CNT-1  on (1) is 8dB attenuation
0x00800000 ATT-CNT-0  on (1) is 16dB attenuation
```

```
0x01000000 PRSG      pseudo random sequence generator on (1), off (0)
0x02000000 RESET     on (1) hold board in reset
0x04000000 SPEC_INV  Enable spectral inversion (1) if needed. see --
```

```

specinv
  0x08000000 TBD          reserved
  0xF0000000 RCU VERSION RCU version, read-only

rspctl [ --rcumode      |
        --rcuprsg      |
        --rcureset     |
        --rcuattenuation |
        --rcudelay     |
        --rcuenable    |
        ]+ [--select=<set>] # control RCU by combining one or more of these
options with RCU selection

        --rcumode=[0..7] # set the RCU in a specific mode
          Possible values: 0 = OFF
                          1 = LBL 10MHz HPF 0x00017900
                          2 = LBL 30MHz HPF 0x00057900
                          3 = LBH 10MHz HPF 0x00037A00
                          4 = LBH 30MHz HPF 0x00077A00
                          5 = HB 110-190MHz 0x0007A400
                          6 = HB 170-230MHz 0x00079400
                          7 = HB 210-270MHz 0x00078400
        --rcuprsg[=0]      # turn psrg on (or off)
        --rcureset[=0]    # hold rcu in reset (or take out of
reset)
        --rcuattenuation=[0..31] # set the RCU attenuation (steps of
0.25dB)
        --rcudelay=[0..127]    # set the delay for rcu's (steps of 5ns
or 6.25ns)
        --rcuenable[=0]      # enable (or disable) input from RCU's

rspctl --specinv[=0] [--select=<set>] # enable (or disable) spectral
inversion

--- Signalprocessing -----
-----
rspctl --weights          [--select=<set>] # get weights as
complex values
  Example --weights --select=1,2,4:7 or --select=1:3,5:7
rspctl --weights=value.re[,value.im] [--select=<set>] [--beamlets=<set>] #
set weights as complex value
rspctl --aweights        [--select=<set>] # get weights as
power and angle (in degrees)
rspctl --aweights=amplitude[,angle] [--select=<set>] # set weights as

```

amplitude and angle (in degrees)

```
rspctl --subbands          [--select=<set>] # get subband
selection
```

```
rspctl --subbands=<set>    [--select=<set>] # set subband
selection
```

Example --subbands sets: --subbands=0:39 or --select=0:19,40:59

```
rspctl --xcsubband        # get the subband
selection for cross correlation
```

```
rspctl --xcsubband=<int>  # set the subband to
cross correlate
```

```
rspctl --wg              [--select=<set>] # get waveform
generator settings
```

```
rspctl --wg=freq [--phase=..] [--amplitude=..] [--select=<set>] # set
waveform generator settings
```

```
--- Status info -----
-----
```

```
rspctl --version          [--select=<set>] # get version information
```

```
rspctl --status          [--select=<set>] # get status of RSP boards
```

```
rspctl --tdstatus        [--select=<set>] # get status of TDS boards
```

```
rspctl --spustatus       [--select=<set>] # get status of SPU board
```

```
rspctl --realdelays[=<list>] [--select=<set>] # get the installed 16
delays of one or more HBA's
```

```
rspctl --regstate        # show update status of all
registers once every second
```

```
rspctl --latency        # show latency of ring and
all lanes
```

```
--- Statistics -----
-----
```

```
rspctl --statistics[=(subband|beamlet)] # get subband (default) or
beamlet statistics
```

```
    [--select=<set>] #
```

```
    [--duration=<seconds>] #
```

```
    [--integration=<seconds>] #
```

```
    [--directory=<directory>] #
```

```
rspctl [--xcangle] --xcstatistics [--select=first,second] # get
crosscorrelation statistics (of pair of RSP boards)
```

```
    [--duration=<seconds>] #
```

```
    [--integration=<seconds>] #
```

```
    [--directory=<directory>] #
```

```
--- Miscellaneous -----
-----
```

```
rspctl --clock[=<int>] # get or set the clock
frequency of clocks in MHz
rspctl --rspclear [--select=<set>] # clear FPGA registers on
RSPboard
rspctl --hbadelays[=<list>] [--select=<set>] # set or get the 16 delays
of one or more HBA's
rspctl --tbbmode[=transient | =subbands,<set>] # set or get TBB mode,
'transient' or 'subbands', if subbands then specify subband set
rspctl --splitter[=0|1] # set or get the status of
the Serdes splitter
rspctl --datastream[=0|1|2|3] # set or get the status of
data stream to cep
rspctl --swapxy[=0|1] [--select=<set>] # set or get the status of
xy swap, 0=normal, 1=swapped
rspctl --bitmode[=4|8|16] # set or get the number of
bits per sample
```