

## Pre-Checks

- Check that the 1pps is connected to the DBBC2
- Check that the 10MHz is connected to the DBBC2
- Check that the IFs are connected (see [Pico DBBC.jpg](#))
- Check that the serial cable is connected from the DBBC to the FiLA10G box
- Check that the GPS antenna is connected to the FiLA10G box
- Check that the GPS antenna is located close to the window or is hanging out of the window
- Check that the USB cable from the DBBC2 backside is **NOT** connected to the FiLA10G box
- Check that all 2 VSI cables are connected to the FiLA10G box (2 coming from the DBBC2, ~~one going to the Mark5B~~)
- ~~Check that one VSI cable of the FiLA10G box is connected to the Mark5 recorder~~

## Startup

- power on the DBBC2 electronics (EL switch)
- power on the DBBC2 PC (PC switch)
- power on the FiLA10G box

## Loading the DBBC2 firmware

- Log into the DBBC2 (user dbbc, password: ask Salvador/Helge); can be done also via remote desktop from mrt-vlbi
- Depending on the observation mode (PFB, or DDC) different firmwares must be used:
- **Polyphase Filterbank Mode (PFB)**
  - On the desktop double-click: "DBBC2 Control PFB v16..." icon (exact name can vary depending on the version)
- **Tunable Mode (DDC)**
  - On the desktop double-click: "DBBC2 Control DDC v107..." icon (exact name can vary depending on the version)
- Reply 'y' to the question whether to configure. Wait until the configuration is finished. During the process the LEDs on the DBBC2 frontside will change. **Leave the window open** after the configuration is finished.
- **Note:** in case the USB cable from the DBBC2 is still plugged into the FiLA10G loading of the firmware will throw an error. Make sure the cable is unplugged!

## Loading the FiLA10G firmware

- Connect the USB cable from the backside of the DBBC2 (top right connector) to the FiLA10G box
- On the Desktop of the DBBC2 double-click the "FiLA10G Load" icon
- Verify that loading of the firmware did not throw errors
- Close the window
- Verify that the LEDs on the frontside of the FiLA10G box are operating (left LED should be red)
- Verify that you can connect to the FiLA10G via the serial line (see section "Communicating with the FiLA10G" below)
- Remove the USB cable from the FiLA10G box

## Communicating with the DBBC2

- On the DBBC2 desktop double click the "DBBC client V4.exe" icon (exact name can depend on the installed software version)
- At the prompt issue a command (a command reference manual can be found in the DBBC2 folder close to the VLBI computer)
- **NOTE: the client must be closed prior to starting the VLBI field system!**

## Communicating with the FiLA10G

- On the DBBC2 desktop double-click the PuTTY icon.
- In PuTTY select the "FiLA10G\_ext" setting and click on open
- In the appearing window hit return to get to the FiLA10G command prompt.
- Enter command at the prompt (a command reference manual can be found in the DBBC2 folder close to the VLBI computer)
- Close PuTTY when done